

HP-A8 V2.10B 追補版 (2013.04.15改訂)

HP-A8 のソフトウェアをV2.10B にアップデートすることにより変更になる機能があります。

本追補版は、以前のバージョンと比べて変更された機能や新たに追加された機能について記述します。製品に付属の取扱説明書、過去に発行された追補版と合わせてお読みください。

・以前のバージョンからの変更点

1. SD カードから、WAV ファイルと AIFF ファイルの再生が可能になりました。

- ・対応サンプリング周波数：44.1K, 48K, 88.2K, 96KHz
- ・対応ビットレート：16Bit, 24Bit, 32Bit
- ・対応フォーマット：リニア PCM

2. 入力セクターの動作を選択できるようになりました。

●INPUT SEL MODE

- ・INCREMENT：従来通り1項目ずつ設定を切り替えます。
- ・DIRECT SELECT：INPUT SEL が表示され、下段にて入力を選択します。

<DIRECT SEL 時の入力選択方法>

- ・本体操作時：
選択する入力を選び、INPUT SEL ボタンを押して入力を確定します。
- ・リモコン操作時：
INPUT SEL ボタンを押し、左右の矢印で入力を選択した後、中央の ENTER ボタン (○) を押して入力を確定します。

直接選択することにより切り替え動作が速くなります。

3. SD カードからの再生モードを選択できるようになりました。

●SD REPEAT MODE

- ・FOLDER：再生中のフォルダー内でループします。
- ・ALL：SD カード内のフォルダーでループします。
- ・SINGLE：再生中のファイルでループします。

4. LCD の ON/OFF が選択できるようになりました。

●LCD ON/OFF

- ・ON：常時 LCD が点灯します。
- ・OFF：約 8 秒間操作されないと LCD が消灯します。

何らかの操作をすると約 8 秒点灯します。

FS が切り替わると約 8 秒点灯します。

MENU 画面中は常時点灯します。

5. 日本語フォルダー名、ファイル名の対応変更

これまでのバージョンでは、フォルダー名やファイル名に日本語が使用されている場合、認識しませんでした。V2.10B では、文字を口にて表示することで認識するようになりました。

V2.10B メニューのパラメータ・リスト

Name	Value	Default	Step
AMP GAIN	0dB to 20dB	0dB	0.5dB
UP Sampling	x1, x2, x4	x1	3
Digital Filter	SHARP ROLL OFF MAXIMUM DELAY	SHARP ROLL OFF	2
MSCK SEL	DIR, XTAL	DIR	2
DIRECT	OFF, ON	OFF	2
IN/VOL MEM	DISABLE INPUT VOLUME INPUT+VOLUME	DISABLE	4
DSD OVER PCM	DISABLE USB	DISABLE	2
USB MUTE SEL	OFF ON	OFF	2
INPUT SEL MODE	INCREMENT DIRECT	INCREMENT	2
SD REPEAT MODE	FOLDER ALL SINGLE	FOLDER	3
LCD ON/OFF	ON OFF	ON	2
SYSTEM INFO	Cur Ver Ver UP RESET	Cur Ver	3

HP-A8 Owner's Manual V2.10B supplement (Issued 2013 Apr. 15)

By updating the HP-A8 software to version 2.10B, there are some changes in operation. This manual supplement describes the functions changed from the previous version and newly added functions. Please read this manual as well as the original owner's manual enclosed in the product and all previously issued manual supplements.

Functions changed from the previous version

1. SD card playback now offers WAV files and AIFF files

- Sampling Frequency: 44.1K, 48K, 88.2K, 96KHz
- Bit Rate: 16, 24, 32bit
- File Format: Linear PCM

2. Quick Input Selector menu is added

• INPUT SEL MODE

- INCREMENT: Same as before, the setting is changed one after another
- DIRECT SELECT: "INPUT SEL" is displayed and choose the input beneath.

<Input select method when DIRECT SEL>

- by the HP-A8 front panel
Choose desired input and then push the INPUT SEL button to set.
- by the remote controller
Push the INPUT SEL button, choose desired input using the right or left arrow button and push the ENTER button (O) in the middle to set.

By the direct select mode, the selector process will become quicker.

3. SD card playback now offers various playback modes

• SD REPEAT MODE

- FOLDER: Playing back the files in loop within the currently chosen folder
- ALL: Playing back the files in loop within all folders in the SD card
- SINGLE: the current file is played back in Loop

4. LCD back light ON or OFF can now be chosen

•LCD ON/OFF

- ON: LCD back light is always ON
- OFF: LCD back light automatically becomes OFF after approx. 8seconds of no operation

V2.10B Parameter Menu list

Name	Value	Default	Step
AMP GAIN	0dB to 20dB	0dB	0.5dB
UP Sampling	x1, x2, x4	x1	3
Digital Filter	SHARP ROLL OFF MAXIMUM DELAY	SHARP ROLL OFF	2
MSCK SEL	DIR, XTAL	DIR	2
DIRECT	OFF, ON	OFF	2
IN/VOL MEM	DISABLE INPUT VOLUME INPUT+VOLUME	DISABLE	4
DSD OVER PCM	DISABLE USB	DISABLE	2
USB MUTE SEL	OFF ON	OFF	2
INPUT SEL MODE	INCREMENT DIRECT	INCREMENT	2
SD REPEAT MODE	FOLDER ALL SINGLE	FOLDER	3
LCD ON/OFF	ON OFF	ON	2
SYSTEM INFO	Cur Ver Ver UP RESET	Cur Ver	3