

HP-A8 V3.00追補版 (2013/11/14発行)

HP-A8 のソフトウェアをV3.00 にアップデートすることにより変更になる機能があります。本追補版は、以前のバージョン(含むベータ版)と比べて変更された機能や新たに追加された機能について記述します。製品に付属の取扱説明書と合わせてお読みください。

以前のベータ・バージョン(V2.13B)からの変更点

1. 本バージョンと同時にリリースするFostex Audio Playerに対応しました。
詳しくはFostex Audio Playerの操作マニュアルを参照ください。
2. MENUで設定していた “DSD OVER PCM”を削除しました。
2013年11月発売予定の新製品 HP-A4における動作と同様に、DoP方式とASIO2.1方式を自動認識します。

※自動認識はWindowsをご使用の場合のみ機能します。
MacはDoPだけの対応となります。

3. メニューに“AUTO POWER OFF”を追加しました。
本機能は欧州省電力規制に対応するために搭載されましたが、日本国内版では動作いたしません。

V3.00 パラメーター・リスト

Name	Value	Default	Step
AMP GAIN	0dB to 20dB	0dB	0.5dB
UP SAMPLING	X1, X2, X4	X1	3
DIGITAL FILTER	SHARP ROLL-OFF(OFF) MINIMUM DELAY	SHARP ROLL-OFF	2
MSCK SEL	DIR (DIRECT) XTAL	DIR	2
DIRECT	OFF, ON	OFF	2
IN/VOL MEM	DISABLE INPUT VOLUME INPUT+VOLUME	DISABLE	4
USB MUTEL SEL	OFF, ON	OFF	2
INPUT SEL MODE	INCREMENT DIRECT SELECT	INCREMENT	2
SD REPEAT MODE	FOLDER ALL SINGLE	FOLDER	3
LCD ON/OFF	ON, OFF	ON	2
AUTO POWER OFF	ON, OFF	ON	2
SYSTEM INFO	Ver_._._ VERSION UP RESET	Ver_._._	3

HP-A8 Owner's Manual V3.00 supplement (issued Nov. 14, 2013)

By updating the HP-A8 software to version 3.00, there are some changes in operation. This manual supplement describes the functions changed from the previous version (incl. from Beta version) and newly added functions. Please read this manual as well as the original owner's manual enclosed in the product.

Functions changed from the previous beta version (V2.13B)

1. The HP-A8 with V3.00 complies with the Fostex Audio Player.
For more details, please refer to the Fostex Audio Player operation manual.
2. The menu "DSD OVER PCM" has been deleted.
The V3.00 automatically recognizes DoP and ASIO 2.1, as the same way as in the HP-A4, which is a new Fostex product to become available Nov. 2013.

*The automatic recognition is only available when using Windows OS.
Mac OS only complies with DoP

3. New menu "AUTO POWER OFF" is added.
Conforming to the ecodesign requirements in the EU territories, when this mode is set to ON, the V3.00 makes HP-A8 automatically turn off the power after incoming audio signal is interrupted more than 30min. Once this mode activates, please push the power SW twice to power on again.

*Depending on the product destination, some HP-A8's do not effect the Auto Power Off funtion due to the difference in the hardware design.

V3.00 Parameter List

Name	Value	Default	Step
AMP GAIN	0dB to 20dB	0dB	0.5dB
UP SAMPLING	X1, X2, X4	X1	3
DIGITAL FILTER	SHARP ROLL-OFF(OFF) MINIMUM DELAY	SHARP ROLL-OFF	2
MSCK SEL	DIR (DIRECT) XTAL	DIR	2
DIRECT	OFF, ON	OFF	2
IN/VOL MEM	DISABLE INPUT VOLUME INPUT+VOLUME	DISABLE	4
USB MUTEL SEL	OFF, ON	OFF	2
INPUT SEL MODE	INCREMENT DIRECT SELECT	INCREMENT	2
SD REPEAT MODE	FOLDER ALL SINGLE	FOLDER	3
LCD ON/OFF	ON, OFF	ON	2
AUTO POWER OFF	ON, OFF	ON	2
SYSTEM INFO	Ver_._._. VERSION UP RESET	Ver_._._.	3